



"Alpha Antenna uses antenna designs that are known to work!"

Alpha Antenna

Model - Ez-Military

6-80 Meters

1KW PEP

USER GUIDE

V1.2

April 29, 2014



"Alpha Antenna uses antenna designs that are known to work!"

Introduction

Thank you for purchasing the Alpha Ez-Military Antenna, a complete 1KW PEP system for Military, Emergency Services, or restricted use environments.

The 1KW Ez-Military system is a Multi-Band antenna from Alpha Antenna that includes a heavy duty Mil-Stick whip the solid state Alpha Match for trouble free operation, and adjustable Alpha Jaw Mount.

Alpha Antenna uses antenna designs that are known to work! Designed by Amateur Radio Operators at Alpha Antenna, in conjunction with a Certified Commercial Broadcast Engineer, the Alpha Ez-Military Antenna uses the best antenna designs in one antenna system.

Technical Specifications

- Weight: 3 pounds
- Configuration: Vertical/Horizontal/NVIS
- Frequency Coverage: 3.8 to 54 MHz
- Power Rating: 1KW PEP SSB
- Height: Approximately 13 Feet



"Alpha Antenna uses antenna designs that are known to work!"

Installation Safety

WARNING: INSTALLATION OF THIS PRODUCT NEAR POWER LINES IS DANGEROUS! FOR YOUR SAFETY, FOLLOW THE ENCLOSED INSTALLATION DIRECTIONS. THOUGH THIS ANTENNA IS CONSTRUCTED OF INSULATED WIRE, PROPER CARE MUST BE TAKEN DURING INSTALLATION. INSTALLER ASSUMES ALL LIABILITY FOR PROPERTY AND LIFE SAFETY.

YOU, YOUR ANTENNA, AND SAFETY

Each year, hundreds of people are killed, mutilated, or receive severe and permanent injuries when attempting to install an antenna. In many of these cases, the victim was aware of the danger of electrocution, but did not take adequate steps to avoid the hazard. For your safety, and to help you achieve a good installation, please **READ** and **FOLLOW** the safety precautions below.

THEY MAY SAVE YOUR LIFE!

1. If you are installing an antenna for the first time, please, for your own safety as well as others, seek PROFESSIONAL ASSISTANCE.
2. Select your installation site with safety, as well as performance, in mind. (Detailed information in Site Selection appears in a separate section of this booklet.) **REMEMBER: ELECTRIC POWER LINES AND PHONE LINES LOOK ALIKE. FOR YOUR SAFETY, ASSUME THAT ANY OVERHEAD LINES CAN KILL YOU.**
3. Call your electric power company. Tell them your plans and ask them to come take a look at your proposed installation. This is a small inconvenience, considering **YOUR LIFE IS AT STAKE.**
4. Plan your installation procedure carefully and completely *before* you begin. Successful raising of a mast or tower is largely a matter of coordination. Each person should be assigned a specific task, and should know what to do and when to do it. One person should be designated as the leader/coordinator of the operation to call out instructions and watch for signs of trouble.
5. When installing your antenna, **REMEMBER: DO NOT USE A METAL LADDER. DO NOT WORK ON A WET OR WINDY DAY. DO DRESS PROPERLY:** shoes with rubber soles and heels, rubber gloves, long sleeved shirt or jacket.
6. If the assembly starts to drop, get away from it and let it fall. Remember, the antenna, mast, cable and metal guy wires are all excellent conductors of electrical current. Even the slightest touch of any of these parts to a power line completes an electrical path through the antenna and the installer – **THAT'S YOU!**
7. If ANY PART of the antenna system should come in contact with a power line, **DON'T TOUCH IT OR TRY TO REMOVE IT YOURSELF. CALL YOUR LOCAL POWER COMPANY.** They will remove it safely. If an accident should occur with the power lines, call for qualified emergency help **IMMEDIATELY.**



"Alpha Antenna uses antenna designs that are known to work!"

Antenna Installation

Step 1 – Install Alpha Jaw Mount on stable support

Step 2 – Screw the Alpha Match into the Jaw Mount

Step 3 – Assemble and screw the whip into the Alpha Match

Step 4 – Attach the counterpoise wire with the supplied nut and screw on the Jaw Mount

Step 5 – Attach a coax to the SO-239 on the Alpha Match that is a minimum of 20 feet in length. Shorter coax or coax that is coiled upon itself to form a choke balun can detune that antenna



"Alpha Antenna uses antenna designs that are known to work!"

SWR Performance

Frequency	SWR
50-54MHz	4.1:1
28-29.7MHz	1.9:1
24.9-25MHz	1.8:1
21-21.5MHz	1.6:1
18.1-18.2MHz	1.8:1
14-14.4MHz	1.7:1
10.1-10.2MHz	2.9:1
7-7.3MHz	2.9:1
5.3305-5.4035MHz	2.6:1
3.8-4MHz	3.4:1



"Alpha Antenna uses antenna designs that are known to work!"

Have Other Questions?

If you have questions about your antenna, please feel free to contact us.

Support

Email: support@alphaantenna.com

Phone: 1-888-482-3249

WEB: www.alphaantenna.com

αANTENNA

"Alpha Antenna uses antenna designs that are known to work!"

Notes:

αANTENNA

"Alpha Antenna uses antenna designs that are known to work!"