O Alpha Antenna

Field Guide SS17+ Antenna

Description:	Assembly:
The PVA VertiTenna is an 8 Band VHF and HF Antenna that	- Screw the telescopic element onto the mount.
covers 2M, 6M, 10M, 12M, 15M, 17M, and 20M.	- Secure the counterpoise/radials to the mount.
Specifications:	Deployment:
Power: Full legal limit	1. Extend the element and adjust it per the tuning chart.
Pattern: Omni-directional	2. Attach your coax and run it 90° from the counterpoise/radials.
RF Connection: SO-239	3. Deploy as a raised/ground mount system with the mount/spike.
Frequency: 220MHz, 440MHz, and 2 to 20 meters	4. Roll the counterpoise out to resonant length when raised; or fully
Ground: Raised/Tuned Counterpoise or Ground Radials	extend both radials in opposite directions when ground mounted.

TUNING CHART (*Raised Counterpoise length may vary based upon different ground conditions.)		
Band	Vertical Element *	Enter Counterpoise length
20 Meters	10 Sections deployed	
17 Meters	8 1/3 Sections deployed	
15 Meters	7 Sections deployed	
12 Meters	6 Sections deployed	
10 Meters	5 Sections deployed	
6 Meters	3 Sections deployed	
2 Meters	2 2/3 Sections	
440MHz	2 feet 2 inches - no counterpoise	
220MHz	2 feet 2 inches & no counterpoise	

How to attach all the options

